



Firma: G Store & Repair doo  
Adresa: Bul.Mihajla Pupina 10z/3  
Telefon: 011 785 66 66  
Fax:  
PIB: 112029009  
E-mail: [office@gstore.rs](mailto:office@gstore.rs)

---

## MB s1200 ASUS PRIME H510M-E

Šifra: 2595

Kategorija proizvoda: Matične ploče

Proizvođač: ASUS

**Cena: 7.750 rsd.**



### Model

<b>Brand</b>	ASUS
<b>Model</b>	PRIME H510M-E

### Supported CPU

<b>CPU Socket Type</b>	LGA 1200
<b>CPU Type</b>	Supports 11th / 10th Gen Intel Core Processors* Supports Intel Pentium Gold and Celeron Processors*  * Refer to <a href="http://www.asus.com">www.asus.com</a> for CPU support list.
<b>Supported CPU Technologies</b>	Supports Intel Turbo Boost Technology 2.0 and Intel Turbo Boost Max Technology 3.0*  * Intel Turbo Boost Max Technology 3.0 support depends on the CPU types.

### Chipsets

<b>Chipset</b>	Intel H510
----------------	------------

### Onboard Video

<b>Onboard Video Chipset</b>	Supported only by CPU with integrated graphic
------------------------------	---

### Memory

<b>Number of Memory Slots</b>	2×288pin
<b>Memory Standard</b>	DDR4 3200(OC) / 2933 / 2800 / 2666 / 2400 / 2133*  * 11th Gen Intel processors support 2933 / 2800 / 2666 / 2400 / 2133 natively. * 10th Gen Intel Core i9 / i7 processors support 2933 / 2800 / 2666 / 2400 / 2133 natively, others will run at the maximum transfer rate of DDR4 2666MHz. * Refer to <a href="http://www.asus.com">www.asus.com</a> for the Memory QVL (Qualified Vendors Lists), and memory frequency support depends on the CPU types.
<b>Maximum Memory Supported</b>	64GB
<b>Channel Supported</b>	Dual Channel

### Expansion Slots

<b>PCI Express 4.0 x16</b>	1 x PCI Express 4.0 x16* * Actual support may vary by CPU.
<b>PCI Express x1</b>	2 x PCIe 3.0 x1

#### Storage Devices

<b>SATA 6Gb/s</b>	4 x SATA 6Gb/s
<b>M.2</b>	Intel H510 Chipset: M.2 slot (Key M), type 2242/2260/2280 (supports PCIe 3.0 x4 & SATA modes)*  * The M.2 slot shares bandwidth with SATA6G_2. When a device in SATA mode is installed on the M.2 slot, SATA6G_2 port cannot be used.

#### Onboard Audio

<b>Audio Chipset</b>	Realtek ALC897/887
<b>Audio Channels</b>	7.1 Channels*  * A chassis with an HD audio module in the front panel is required to support 7.1 Surround Sound audio output.

#### Onboard LAN

<b>LAN Chipset</b>	Intel I219-V
<b>Max LAN Speed</b>	10/100/1000Mbps

#### Rear Panel Ports

<b>Back I/O Ports</b>	2 x USB 3.2 Gen 1 ports (2 x Type-A) 2 x USB 2.0 ports (2 x Type-A) 1 x DisplayPort 1 x D-Sub port 1 x HDMI port 1 x Intel I219-V 1Gb Ethernet port 3 x Audio jacks 1 x PS/2 Keyboard (purple) port 1 x PS/2 Mouse (green) port
-----------------------	---

#### Internal I/O Connectors

<b>Onboard USB</b>	1 x USB 3.2 Gen 1 header supports additional 2 USB 3.2 Gen 1 ports 2 x USB 2.0 headers support additional 4 USB 2.0 ports
<b>Other Connectors</b>	Fan and Cooling related 1 x 4-pin CPU Fan header 1 x 4-pin Chassis Fan header Miscellaneous 1 x RGB header 1 x Clear CMOS header 1 x COM Port header 1 x Front Panel Audio header (AAFP) 1 x S/PDIF Out header 1 x Speaker header 1 x SPI TPM header (14-1pin)